

WHITE SHARK



CADOR
GAMING MOUSE

User manual

SPECIFICATIONS

- * Mouse type: 6D - 6 buttons
- * Interface: BT + 2.4 GHz Wireless + Wired
- * Chipset: Instant S203
- * Sensor type: Optical
- * Resolution: 6400 DPI (10,000 DPI software Interpolated)
- * Polling rate: 1000 Hz (BT: 133 Hz)
- * Track speed: 60 IPS
- * Acceleration: 20 G
- * Framerate: 4800 fps
- * Switches: Huano 50 mil. times
- * Battery: Li-Polymer 500 mAh
- * Software: Yes
- * Illumination: RGB 16.8 mil. colors
- * Cable length: 1.5 m - Paracord
- * Dimensions: 120 x 67 x 38 mm
- * Weight: 69 g ±3 g (Without USB receiver)
- * Honeycomb: 67 g ±3 g (Without USB receiver)
- * Compatibility: Win 7 / 8 / 10 / 11 / Mac OS
- * Color: Black, White, Honeycomb Black
- * Material: ABS Plastic

EN-1

Other button function:

1. DPI button (Switch DPI, when using BT mode, press and hold the DPI button for more than 3 seconds to enter into BT pairing mode.)
2. Left button+ right button + middle scroll wheel (press and hold for 3 seconds) = Restore factory settings
3. Left button + Right button (press and hold for 3 seconds) to switch polling rate. After successful switch, the light color is: 125Hz (Red) - 250Hz (Green) - 500Hz (Blue) - 1000Hz (Purple)
4. Bottom switch: 2.4G (left) / OFF (middle) / BT (right).



Connection mode

Wired mode:

Connect to wired mode while charging the mouse by inserting the data cable.

2.4G mode:

1. 2.4G indicator light flashes green at the bottom of the mouse.
2. 2.4G indicator light flashes to indicate reconnection, flashing slowly once every 2 seconds, and total of 5 flashes, then stopping after 10 seconds.
3. 2.4G pairing time: 30 seconds
4. Plug the 2.4GHz USB dongle into the free USB port of computer or laptop, dial the bottom switch to 2.4 GHz mode position, after successful connection, then can use 2.4 GHz mode normally.

BT mode:

1. Bluetooth indicator flashes blue light at the bottom of the mouse (it shares the same lighting effect as the breathing light).
2. BT indicator light flashes to indicate reconnection, flashing slowly once every 2 seconds, and total of 5 flashes, then stopping after 10 seconds.
3. BT pairing time: 120 seconds.
4. When to use the BT mode, switch the bottom switch to BT mode position, press and hold the DPI button for 3 seconds until the mouse's blue light flashes rapidly to enter BT pairing mode. Turn on BT on your computer, search for the "CADOR" BT name, click connect, and it's ready to use after successful pairing.
5. When to switch to BT mode without take off the 2.4G USB dongle on the computer, dial the bottom switch to BT mode, press and hold the DPI button for 3 seconds to enter Bluetooth pairing mode, and click the "CADOR" BT name to pair. After pair successfully, then can use BT mode.

EN-2

6. After successfully connecting in BT mode, if you want to switch back to 2.4GHz mode, simply dial the bottom switch to 2.4 GHz mode, then can use normally. However, if you want to switch back to BT mode again, there are two ways:

-If the BT pairing connection record on the computer has not been deleted, dial the switch from 2.4GHz mode to BT mode will automatically reconnect.
-If the BT connection record was deleted on the computer, BT will not automatically reconnect. You need to repeat the following steps: dial the bottom switch to BT position → press and hold the DPI button for 3 seconds to enter BT pairing mode → Computer BT ON → click the "CADOR" BT name to connect. After successful pairing, you can use BT mode.

Charging indicator light:

The red light at the middle transparent shell and bottom stays on while charging and returns to normal light effect when fully charged.

Power management:

A low voltage warning light will flash red when the voltage drops below DC 3.3 V. The mouse will stop working when voltage is at DC 3.0 V.

Light effect switching:

The lighting effects are designed to be marquee light. Press the side button + middle scroll wheel to switch the light effect (11 kinds light effect+ light off).

Sleep mode:

Sometimes, if the mouse is inactivity for a long time, the mouse will enter into sleep mode. At this time, you need to wake up the mouse first, then to switch 2.4G or BT using mode.

The mouse enters into level 1 sleep status after 60 seconds of inactivity. It supports waking up by moving the mouse 10 minutes before the mouse entering into level 1 sleep status.

And the mouse enters into a deep sleep status after 10 minutes inactivity, then only can be wake-up by clicking the mouse button.

EN-3

WHITE SHARK

EC REP

ŠMIT ELECTRONIC d.o.o.
Metanska 1, KUTINA, CROATIA
Tel. +38544680704
info@smitelectronic.hr

Product name: BT / 2.4GHz Wireless Mouse
Model: CADOR
Battery capacity: 500 mAh Li-Polymer
Rated voltage: 3.7 V
Rated current: 30 mA
S/N Production batch number: WGM5020122025



Manufacturer: SBOX TECHNOLOGY LTD, FLAT 906, 9/F., WORKINGPORT COMM. BLDG., 3 HAUFOOK ST. TSIM SHA TSUI, KOWLOON, HONG KONG, hello@whiteshark.gg, www.whiteshark.gg Made in China.

WHITE SHARK



WHITE SHARK



CADOR
GAMING MOUSE

Upute

KARAKTERISTIKE

- * Tip miša: 6D - 6 tipki
- * Sučelje: BT + 2.4 GHz Wireless + žično
- * Chipset: Instant S203
- * Tip senzora: Optički
- * Rezolucija: 6400 DPI (10,000 DPI interpolirano putem softwera)
- * Polling rate: 1000 Hz (BT: 133 Hz)
- * Brzina praćenja: 60 IPS
- * Ubrzanje: 20 G
- * Framerate: 4800 fps
- * Prekidači: Huano - preko 50 mil. klikova
- * Baterija: Li-Polimer 500 mAh
- * Software: Da
- * Osvjetljenje: RGB 16.8 mil. colors
- * Duljina kabla: 1.5 m - Paracord
- * Dimenzije: 120 x 67 x 38 mm
- * Težina: 69 g ±3 g (Bez USB prijemnika)
- * Honeycomb: 67 g ±3 g (Bez USB prijemnika)
- * Kompatibilnost: Win 7 / 8 / 10 / 11 / Mac OS
- * Boja: crna, bijela, crna s honeycomb rupicama
- * Materijal: ABS plastika

HR-1

Funkcija ostalih tipki:

1. DPI tipka (Prebacivanje DPI-ja; kada se koristi BT način rada, pritisnite i držite DPI tipku više od 3 sekunde kako biste ušli u BT način uparivanja).
2. Lijeva tipka + desna tipka + srednji kotačić za pomicanje (pritisnuti i držati 3 sekunde) - Vraćanje tvorničkih postavki.
3. Lijeva tipka + desna tipka (pritisnuti i držati 3 sekunde) za prebacivanje stope ispitivanja (polling rate). Nakon uspješnog prebacivanja, boja svjetla je: 125 Hz (crvena) - 250 Hz (zeleno) - 500 Hz (plava) - 1000 Hz (ljubičasta).
4. Donji prekidač: 2.4G (lijevo) / OFF (sredina) / BT (desno).



Načini povezivanja

Žičani način rada:

Spojite se na žičani način rada u bilo kojem trenutku dok se miš puni tako što ćete umetnuti podatkovni kabel.

2.4G način rada:

1. 2.4G indikator treperi zelenim svjetlom na dnu miša.
2. 2.4G indikator treperi kako bi označio ponovno povezivanje, trepereći sporo jednom svake 2 sekunde, ukupno 5 treptaja, zatim se zaustavlja nakon 10 sekundi.
3. Vrijeme uparivanja za 2.4G je 30 sekundi.
4. Umetnite 2.4 GHz USB prijemnik u slobodni USB priključak računala ili prijenosnog računala, prebacite donji prekidač u položaj 2,4 GHz načina rada; nakon uspješnog povezivanja moguće je normalno koristiti 2,4 GHz način rada.

BT način rada:

1. Bluetooth indikator treperi plavim svjetlom na dnu miša (dijeli isti svjetlosni efekt kao i "breathing light").
2. BT indikator treperi kako bi označio ponovno povezivanje, trepereći sporo jednom svake 2 sekunde, ukupno 5 treptaja, zatim se zaustavlja nakon 10 sekundi.
3. Vrijeme uparivanja za BT je 120 sekundi
4. Kada želite koristiti BT način rada, prebacite donji prekidač u položaj BT načina rada, pritisnite i držite DPI tipku 3 sekunde dok plavo svjetlo miša ne počne brzo treperiti kako biste ušli u BT način uparivanja. Uključite BT na svom računalu, potražite BT naziv „CADOR“; kliknite na povezivanje i uređaj je spreman za korištenje nakon uspješnog uparivanja.
5. Kada želite prebaciti na BT način rada bez uklanjanja 2.4G USB prijemnika s računala, prebacite donji prekidač u BT način rada, pritisnite i držite DPI tipku 3 sekunde kako biste ušli u Bluetooth način uparivanja, te kliknite BT naziv „CADOR“ za uparivanje. Nakon uspješnog uparivanja moguće je koristiti BT način rada.
6. Nakon uspješnog povezivanja u BT načinu rada, ako se želite vratiti na 2,4 GHz način rada, jednostavno prebacite donji prekidač u položaj 2,4 GHz i uređaj se može normalno koristiti. Međutim, ako se ponovno želite vratiti na BT način rada, postoje dva načina:

HR-2

- Ako zapis o BT uparivanju na računalu nije izbrisan, prebacivanje prekidača s 2,4 GHz načina rada na BT način rada automatski će ponovno uspostaviti vezu.

- Ako je zapis o BT povezivanju izbrisan na računalu, BT se neće automatski ponovno povezati. Potrebno je ponoviti sljedeće korake: prebacite donji prekidač u BT položaj → pritisnite i držite DPI tipku 3 sekunde kako biste ušli u BT način uparivanja → uključite BT na računalu → kliknite BT naziv „CADOR“ za povezivanje. Nakon uspješnog uparivanja možete koristiti BT način rada.

Indikator punjenja:

Crveno svjetlo na srednjoj prozirnoj ljusci i na dnu stalno svijetli tijekom punjenja i vraća se na normalni svjetlosni efekt kada je potpuno napunjen.

Upravljanje napajanjem:

Svjetlo upozorenja na nisku razinu napona treptat će crveno kada napon padne ispod DC 3.3 V. Miš će prestati raditi kada je napon na DC 3.0 V.

Prebacivanje svjetlosnog efekta:

Svjetlosni efekti su dizajnirani kao "marquee light". Pritisnite bočnu tipku + srednji kotačić za pomicanje kako biste prebacili svjetlosni efekt (11 vrsta svjetlosnih efekata + isključeno svjetlo).

Način mirovanja (Sleep mode):

Ponekad, ako je miš dulje vrijeme neaktivan, ući će u način mirovanja. U tom slučaju potrebno je najprije probuditi miš, a zatim prebaciti na 2,4G ili BT način rada.

Miš ulazi u stanje mirovanja razine 1 nakon 60 sekundi neaktivnosti.

Podržava buđenje pomicanjem miša 10 minuta prije nego što miš uđe u mirovanje razine 1. Miš ulazi u duboko stanje mirovanja nakon 10 minuta neaktivnosti, te se tada može probuditi samo klikom na tipku miša.

WHITE SHARK

EC REP

ŠMIT ELECTRONIC d.o.o.
Metanska 1, KUTINA, CROATIA
Tel. +38544680704
info@smitelectronic.hr

Product name: BT / 2.4GHz Wireless Mouse
Model: CADOR
Battery capacity: 500 mAh Li-Polymer
Rated voltage: 3.7 V
Rated current: 30 mA
S/N Production batch number: WGM5020122025



Manufacturer: SBOX TECHNOLOGY LTD, FLAT 906, 9/F., WORKINGPORT COMM. BLDG., 3 HAUFOOK ST. TSIM SHA TSUI, KOWLOON, HONG KONG, hello@whiteshark.gg, www.whiteshark.gg Made in China.

HR-3

WARRANTY CARD / JAMSTVENI LIST

ITEM/MODEL: Naziv/model proizvoda:	
RECEIPT NO. / DATE OF PURCHASE: Broj i datum računa:	
SELLING SPOT (COMPANY): Prodajno mjesto:	
THE CUSTOMER: Kupac:	
WARRANTY PERIOD (MONTHS): Jamstveni rok (Mjeseci):	36
SIGNATURE / STAMP: Potpis i pečat:	

All White Shark products are examined and tested after each stage of the production process and have all the required certificates (EMC, CE, ...). The products are subject to the following warranty conditions: - The warranty period for White Shark products is 36 months (on batteries 6 months) and begins on the day of being sold in the store. - The warranty can only be claimed upon presentation of the original purchase invoice and a filed warranty paper with a stamp from the store it was bought at, and if the product has original packaging and all components and equipment. - All malfunctioning of the product resulting from factory defects, that occur during the warranty period, and in the normal use of the product in compliance with all instructions will be removed. This warranty covers only defects in material and production. - If the product malfunctions during the warranty period, your White Shark distributor will give you the product (after which is checked by a professional) repaired or replaced. - If the repair at the authorized service center is not completed within 30 days of being received at the service center, we will replace the product with a new one. If the repair during the warranty period lasts longer than 15 days, the warranty period is extended by as many days as the repair lasted. - If the device needs to be repaired within the warranty period, contact the store where you bought the product. If the product has to be sent to an authorized service center or general distributor, please send the product (with all parts and accessories) in the original packaging and with all the necessary documents (invoice, warranty card, etc.). The product can be repaired only in the authorized service center of the importer. The costs of shipping the product to the service center are funded by the customer. Possible damage to the product that can occur during transport is at the expense and risk of the buyer. Sending the product from the service center to the customer is funded by the service technician/the importer. This warranty does NOT cover: - Damage or malfunctions that would occur as a result of incorrect connection, incorrect polarization, incorrect battery placement, etc. - Defects caused by improper handling of products, use of parts or equipment that is not prescribed by our specifications, unauthorized product modification, and defects mechanical damage to the product. - Defects that can occur due to product fall, use of force, natural disasters (flood, fire, thunder, earthquake, ...), due to battery leakage, due to unstable 220V voltage, frequent variations and/or power outages, etc. - Damage caused during transport to the customer. - Products that have been opened or repaired by an unauthorized person. - Parts that are considered consumables such as batteries, etc.

Svi White Shark proizvodi su provjereni i testirani nakon svake faze proizvodnog procesa te imaju sve potrebne certifikate (EMC, CE, ...) te podliježu sljedećim jamstvenim uvjetima: - Jamstveni rok na White Shark proizvode je 36 mjeseci (na baterije 6 m) i počinje teći danom prodaje u trgovini. - Jamstvo se može ostvariti samo uz predočenje originalnog računa o kupnji i uredno popunjenog jamstvenog lista - sa žigom trgovine, te ako proizvod ima originalnu ambalažu i sve sastavne dijelove i opremu. - Svi nedostaci i kvarovi koji su posljedica tvorničkih grešaka i koji su nastali u jamstvenom roku i pri normalnoj uporabi proizvoda i pri postavljanju svih naputaka će biti otklonjeni. Ovo jamstvo obuhvaća samo greške nastale u materijalu i izradi. - Ako se proizvod pokvari tijekom jamstvenog roka, Vaš White Shark distributer će Vam proizvod popraviti ili zamijeniti nakon što ga provjeri stručna osoba - Ako popravak u ovlaštenom servisu nije izvršen u roku 30 dana od primitka u servis, proizvod ćemo zamijeniti novim. U slučaju da popravak u jamstvenom roku traje duže od 15 dana, jamstveni rok se produžuje za onoliko dana koliko je popravak trajao. - Ako se ukazuje potreba popravka uređaja u jamstvenom roku, kontaktirajte trgovinu u kojoj ste proizvod kupili. Ako proizvod treba poslati ovlaštenom servisu ili generalnom distributeru, molimo Vas da kompletan proizvod (sa svim dijelovima i opremom) bude zapakiran u originalnu ambalažu te da priložite sve potrebne dokumente (račun i ovjereni jamstveni list). Popravak aparata vrši se isključivo u ovlaštenom servisu uvoznika. Troškove prijevoza proizvoda na servis snosi kupac. Kupac preuzima rizik za moguća oštećenja tijekom prijevoza. Slanje proizvoda od servisa do kupca snosi serviser tj. uvoznik. Ovo jamstvo NE obuhvaća: - Oštećenja ili kvarove koji su nastali kao posljedica nepravilnog priključivanja, krive polarizacije, pogrešnog stavljanja baterija i sl. - Kvarove nastale zbog nepropisanog rukovanja proizvodom, korištenja dijelova ili opreme koja nije propisana našim specifikacijama, neovlaštenog modificiranja proizvoda te kvarove nastale mehaničkim oštećenjem proizvoda - Kvarove koji mogu nastati uslijed pada proizvoda, uporabe sile, više sile tj. elementarnih nepogoda (poplava, požar, grom, potres, ...), uslijed curenja baterije, uslijed nestabilnog 220V napona, čestih varijacija i/ili nestanaka struje i sl. - Oštećenja nastala pri prijevozu do kupca - Proizvod koji je otvoren i/ili popravljan od strane neovlaštene osobe - Dijelove koji se smatraju potrošnim kao što su baterije i sl.

WHITE SHARK

HR-4